



MATERIAL FACT SHEET

243781 FR-D720-11K

General Data

Product Hierarchy	IAK23701
	INVERTER
	FR-D720
Ext. Material Group	10 EOL ANNOUNCED
ABC Indicator	C (Non-Stock Material / Make-to-Order)

e-shop: <https://emea.mitsubishielectric.com/fa/shop/material-page/000000000000243781>

FA-Inverter: Inverter

Series	FR-D700 SERIES
Type	FR-D700 COMPACT INVERTER
Minimum Rated Voltage (V)	200
Min. Permissible Voltage (V)	170
Maximum Rated Voltage (V)	240
Max. Permissible Voltage (V)	264
Current Type	AC
Phases	3
Rated Output Current ND (A)	45
Rated Motor Capacity ND (kW)	11
Frequency Range (Hz)	-
Control Method	MAGNETIC FLUX VECTOR CONTROL
Control Method (2)	SOFT-PWM/HIGH FREQUENCY PWM
Control Method (3)	V/F CONTROL
Motor Type	INDUCTION MOTOR
Brake Chopper ED (%)	30
Integrated EMC Filter	NO
Safe Torque Off (STO)	YES
Regenerative (4Q)	NO
Integrated DC Choke	NO
Display	BUILT-IN
Display Type	4 DIGITS LED
PLC Function	NO
Integrated Digital Inputs	5
Digital Outputs (Transistor)	1
Digital Outputs (Relay)	1
Integrated Analogue Inputs	2
Integrated Analogue Outputs	1
IO Type of Terminal Block	SPRING CLAMP
Expandable	NO
RS-485	1
USB	NO
Ethernet Port	NO
Built-In Network	MODBUS-RTU
Leakage Current (mA)	1
Power Loss ND (W)	520
Standby Power Consumption (W)	13-22,5
Protection Class	IP20

Product Dimensions & Weight

Width (mm)	220
Height (mm)	260
Depth (mm)	190
Weight (kg)	6,5

Logistic Dimensions & Gross Weight

Length (cm)	27,5
-------------	------

Width (cm)	35,5
Height (cm)	29,0
Gross Weight (kg)	7,561
Volume (cdm)	28,311

Stock Data

Planned Delivery Time (Days)	175
------------------------------	-----

Life Cycle

Sales Start	17.08.2011
Discontinued (EOL)	01.01.2026
Last Time Buy (LTB)	31.12.2026
Last Time Purchase (LTP)	31.01.2027
End of Service (EOS)	31.01.2034
Predecessor	No Predecessor
Successor	757564 / FR-D820-11K-450-60

Additional Product Information

Difference to Standard 1	JAPANESE VERSION
Binding Tariff Information	DEBTI-14477/24-1
BTI validity date	07.07.2027
Battery included	NO
Product Code	INV(EXCEPT VECTOR INV)

Export Data

Commodity Code	85044095
Legal Control (Dual Use List)	Not Listed
Country of Origin	Japan (JP)
Preference Status (Supplier Declaration)	Non EU

Environmental

REACH Limit Exceeded	YES
REACH Substance CAS Number	-
REACH Substance CAS Number (2)	108-78-1
REACH Substance CAS Number (3)	119-47-1
REACH Substance CAS Number (4)	119313-12-1
REACH Substance CAS Number (5)	12060-00-3
REACH Substance CAS Number (6)	15571-58-1
REACH Substance CAS Number (7)	25155-23-1
REACH Substance CAS Number (8)	3147-75-9
REACH Substance CAS Number (9)	540-97-6
REACH Substance CAS Number (10)	541-02-6
REACH Substance CAS Number (11)	556-67-2
REACH Substance CAS Number (12)	71868-10-5
REACH Substance CAS Number (13)	7439-92-1
REACH Substance CAS Number (14)	79-94-7
REACH Substance CAS Number (15)	80-05-7
REACH Substance CAS Number (16)	872-50-4
REACH Substance CAS Number (17)	9036-19-5
REACH Substance CAS Number (18)	96-45-7
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	COMPLIANT
UKCA	COMPLIANT

Documentation & Media Data

Manual URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=bltdae25c2bd5f2ff94&q=FR-D720-11K&doc-lang=en
Certificates URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt8050dd1408c11cc2&q=FR-D720-11K&doc-lang=en
CAD URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt26ecc97a31a841c1&q=FR-D720-11K&doc-lang=en

Product Packaging

Cardboard (g)	1160
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	10
Wood (g)	0
Glass (g)	0
Others (g)	0

Spare parts

Material	Description	Quantity	Unit
164631	FR-F740-00170-00380 FAN	2	PC
164655	FR-F740-00170-00380 FAN COVER	1	PC

Compatible products

Material	Description / Price List Text / Classification
70727	FR-A5 CBL 1 Cable for connecting Inverter and Programming panel; 1m Class 100100405: FA-Inverter: Cable
70728	FR-A5 CBL 3 Cable for connecting Inverter and Programming panel; 3m Class 100100405: FA-Inverter: Cable
70729	FR-A5 CBL 5 Cable for connecting Inverter and Programming panel; 5m Class 100100405: FA-Inverter: Cable
88426	SC-FR-PC CONNECTION CABLE PC>INVERTER Programming Cable RS 232>RS485/422; 5m Class 100100405: FA-Inverter: Cable
130832	FR-UDA02 DIN-Rail Adaptor for FR-D720S-1,5k; FR-D740-0,4k-3,7k Class 100100403: FA-Inverter: External Option
157514	FR-DU07 Parameter Unit for inverter type FR-A700-NA Class 100100403: FA-Inverter: External Option
157515	FR-ADP Adaptor Module for Operator Panel FR-DU07 Class 100100403: FA-Inverter: External Option
166134	FR-PU07 Programming panel with LCD-Display for all units of FR-700 series Class 100100403: FA-Inverter: External Option
209052	FR-PU07BB-L Programming Panel with Copy Function; batterypowered; all FR-700 units; w/o bat. Class 100100403: FA-Inverter: External Option
209740	FFR-SI-48A-SS1 Sinusfilter for 200/400V Inverters; max. 48A; FT=4-16kHz; (W*H*D) 240*290*210mm Class 100100404: FA-Inverter: Filter
209757	FFR-DT-47A-SS1 du/dt Filter for 400V Inverters; max. 47A; FT=2-16kHz; (W*H*D) 155*195*110mm Class 100100404: FA-Inverter: Filter
214795	FR-PA07 Simple Parameter Unit for mounting on enclosure surface; for all FR-E700 Class 100100403: FA-Inverter: External Option
254840	NF125-SV 3P 75A Circuit breaker 3pole. In = 75A; Icu = Ics = 25kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
275503	FR Configurator-M+FR-Configurator2 FR-Configurator for 700 series; multi I + FR-Configurator2 for 800 series Class 100101203: FA-Software: Software Inverter
283576	FFR-HEL-11K-E1 DC Link choke for 200V Inverter; 11kW; 0,6mH; 48A Class 100100406: FA-Inverter: Choke
298657	S-T35 AC200V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298658	S-T35 AC24V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 24V, 50Hz Class 100101001: FA-MC: Magnetic Contactor